



1. The two-post Keyboard+Tray mounts to any rack with 3"- or 6"-wide channels and requires only 1 RMU of available space. (Illustration shows rack with 3" channels.)
2. When you select the mounting location, consider the cable distance between the tray and the active equipment you have installed. Also, your desired mounting height will depend on whether you plan to use the keyboard while sitting or standing.

3. Place the brackets on the rails of the tray. Use the #8 screws provided to hold this placement, but do not tighten the screws.
4. Position the tray between the rack channels at your desired mounting location.
5. Use the #12 screws provided to attach the tray to the rack.
6. If you desire, you can now adjust the tray at 1-inch increments forward or backward by sliding the rails along the brackets.
7. Tighten the screws holding the brackets to the rails.
8. Place the keyboard on the tray.
9. Route keyboard cable behind the cable retention post as shown in detail A.
10. Use the cable tie provided to hold keyboard cable to wire manager.
11. Remember to send in the warranty card or fill out the product registration online at www.chatsworth.com/prodreg.html.

Thank you for purchasing quality products from Chatsworth Products, Inc.

CPI CHATSWORTH PRODUCTS, INC.

**INSTALLATION INSTRUCTION,
KEYBOARD TRAY,
2 POST,19"W**

THIS DRAWING CONTAINS INFORMATION PROPRIETARY TO CHATSWORTH PRODUCTS, INC. ANY REPRODUCTION DISCLOSURE OR USE OF THIS DRAWING IS EXPRESSLY FORBIDDEN EXCEPT AS AGREED TO IN WRITING BY CHATSWORTH PRODUCTS, INC.