



1. The two-post Monitor Shelf mounts to any rack with 3"- or 6"-wide channels. (Illustration shows rack with 3" channels.)
2. When you select the mounting location, consider the cable distance between the shelf and the active equipment you have installed. Also, your desired mounting height will depend on whether you plan to use the monitor while sitting or standing.
3. Place the brackets on the rails of the shelf. Use the #10 screws provided to hold this placement, but do not tighten the screws.
4. Position the shelf between the rack channels at your desired mounting location.

5. Use the #12 screws provided to attach the shelf to the rack. Tighten all screws.
6. Attach the Cable Clip to the back of the monitor (as shown above) and then, route the Video cable through it.
7. Using the provided Velcro, secure the power adaptor to the shelf. Also tie-wrap all of the cables to the wire manager in the back.
8. Make sure the shelf is moving in and out freely without putting tension on the cables.

Thank you for purchasing quality products from chatsworth products, inc.

CPI CHATSWORTH PRODUCTS, INC.

**INSTALLATION INSTRUCTION,
LCD MONITOR SHELF,
2 POST, 19"W**

THIS DRAWING CONTAINS INFORMATION PROPRIETARY TO CHATSWORTH PRODUCTS, INC. ANY REPRODUCTION DISCLOSURE OR USE OF THIS DRAWING IS EXPRESSLY FORBIDDEN EXCEPT AS AGREED TO IN WRITING BY CHATSWORTH PRODUCTS, INC.